

GOODWE

ES Series

5kW | Single Phase Hybrid Inverter

The GoodWe ES series of bi-directional energy storage inverters can be used for both on-grid and off-grid PV systems, with the ability to control the flow of energy intelligently. During the day, the PV array generates electricity which can be provided either to the loads, fed into the grid, or charge the battery, depending on the economics and set-up. The electricity stored can be released when the loads require it during the night, including inductive loads such as air conditioners or refrigerators. Additionally, the power grid can also charge storage devices via the inverter. An all-round intelligent system for maximum energy flexibility.



Charge controller and inverter integrated



Maximum charge and discharge up to 100A



Export control (Zero export)



IP65 dustproof and waterproof



8 ms UPS-level Switching



Fanless design, long lifespan

| Technical Data | GW3648D-ES ⁷ GW3648C-ES ⁷ | GW5048D-ES ⁸ GW5048C-ES ⁸ |
|---|--|--|
| Battery Input Data | | |
| Battery Type | Li-Ion | Li-Ion |
| Nominal Battery Voltage (V) | 48 | 48 |
| Max. Continuous Charging Current (A) ¹ | 75 | 100 |
| Max. Continuous Discharging Current (A) ¹ | 75 | 100 |
| PV String Input Data | | |
| Max. Input Power (W) | 4950 | 6700 |
| Max. Input Voltage (V) | 580 | 580 |
| MPPT Operating Voltage Range (V) | 125~550 | 125~550 |
| Start-up Voltage (V) | 125 | 125 |
| Nominal Input Voltage (V) | 360 | 360 |
| Max. Input Current per MPPT (A) | 11/11 | 11/11 |
| Max. Short Circuit Current per MPPT (A) | 13.8/13.8 | 13.8/13.8 |
| Number of MPP Trackers | 2 | 2 |
| Number of Strings per MPPT | 1 | 1 |
| AC Output Data (On-grid) | | |
| Nominal Apparent Power Output to Utility Grid (VA) ⁵ | 3680 | 5000 |
| Max. Apparent Power Output to Utility Grid (VA) ² | 3680 | 5000 |
| Max. Apparent Power from Utility Grid (VA) | 7360 | 9200 |
| Nominal Output Voltage (V) | 230 | 230 |
| Nominal AC Grid Frequency (Hz) | 50/60 | 50/60 |
| Max. AC Current Output to Utility Grid (A) | 16 ⁶ | 24.5 |
| Max. AC Current From Utility Grid (A) | 32 | 40 |
| Power Factor | ~1 (Adjustable from 0.8 leading to 0.8 lagging) | |
| Max. Total Harmonic Distortion | <3% | <3% |
| AC Output Data (Back-up) | | |
| Back-up Nominal Apparent Power (VA) | 3680 | 4600 |
| Max. Output Apparent Power (VA) ³ | 3680 | 4600 |
| Max. Output Current (A) | 16 | 20 |
| Nominal Output Voltage (V) | 230 (± 2%) | 230 (± 2%) |
| Nominal Output Frequency (Hz) | 50/60 (± 0.2%) | 50/60 (± 0.2%) |
| Output THDv (@Linear Load) | <3% | <3% |
| Efficiency | | |
| Max. Efficiency | 97.6% | 97.6% |
| European Efficiency | 97.0% | 97.0% |
| Max. Battery to AC Efficiency | 94.0% | 94.0% |
| MPPT Efficiency | 99.9% | 99.9% |
| Protection | | |
| PV Insulation Resistance Detection | Integrated | Integrated |
| Residual Current Monitoring | Integrated | Integrated |
| PV Reverse Polarity Protection | Integrated | Integrated |
| Anti-islanding Protection | Integrated | Integrated |
| AC Overcurrent Protection | Integrated | Integrated |
| AC Short Circuit Protection | Integrated | Integrated |
| AC Overvoltage Protection | Integrated | Integrated |
| General Data | | |
| Operating Temperature Range (°C) | -25~60 | -25~60 |
| Relative Humidity | 0~95% | 0~95% |
| Max. Operating Altitude (m) | 3000 | 3000 |
| Cooling Method | Natural Convection | Natural Convection |
| Display | LED & APP | LED & APP |
| Communication with BMS ⁴ | RS485; CAN | RS485; CAN |
| Communication with Meter | RS485 | RS485 |
| Communication with Portal | Wi-Fi | Wi-Fi |
| Weight (Kg) | 28 | 30 |
| Dimension (W x H x D mm) | 516 x 440 x 184 | 516 x 440 x 184 |
| Noise Emission (dB) | <25 | <25 |
| Topology | Battery Isolation | Battery Isolation |
| Self-consumption at Night (W) | <13 | <13 |
| Ingress Protection Rating | IP65 | IP65 |
| Mounting Method | Wall Bracket | Wall Bracket |
| Country of Manufacture | China | China |

¹: The actual charge and discharge current also depends on the battery.
²: 4600 for VDE 0126-1-1 & VDE-AR-N4105 & NRS 097-2-1, 5100 for CEI 0-21 (GW5048D-ES); 4050 for CEI 0-21 (GW3648D-ES).
³: Peak output apparent power can be reached only if PV and battery power is enough.
⁴: CAN communication is configured by default. If 485 communication is used, please replace the corresponding communication line.
⁵: 4600 for VDE 0126-1-1 & VDE-AR-N4105 & NRS 097-2-1, 4600 for CEI 0-21 (GW5048D-ES).
⁶: 18 for CEI 0-21.

⁷: FOR AUSTRALIA ONLY. Model GW3648D-ES inverters are designed without DC switch. For inverters designed with DC switch, the model name should be GW3648C-ES.
⁸: FOR AUSTRALIA ONLY. Model GW5048D-ES inverters are designed without DC switch. For inverters designed with DC switch, the model name should be GW5048C-ES.
*: Under off-grid mode, then battery capacity should be more than 100Ah.
*: When there is no battery connected, inverter starts feeding in only if string voltage is higher than 200V.
*: Please visit GoodWe website for the latest certificates.